
Plyer Documentation

Release 1.4.3

Mathieu Virbel, Akshay Aurora, Gabriel Petier, Ben Rousch

Jul 23, 2022

Contents

1	Plyer	3
2	Facades	5
3	Indices and tables	17
	Python Module Index	19
	Index	21

Plyer is a Python library for accessing features of your hardware / platforms.

CHAPTER 1

Plyer

```
plyer.accelerometer = <plyer.platforms.linux.accelerometer.LinuxAccelerometer object>
    Accelerometer proxy to plyer.facades.Accelerometer

plyer.audio = <plyer.facades.audio.Audio object>
    Audio proxy to plyer.facades.Audio

plyer.barometer = <plyer.facades.barometer.Barometer object>
    Barometer proxy to plyer.facades.Barometer

plyer.battery = <plyer.facades.battery.Battery object>
    Battery proxy to plyer.facades.Battery

plyer.bluetooth = <plyer.facades.bluetooth.Bluetooth object>
    Bluetooth proxy to plyer.facades.Bluetooth

plyer.brightness = <plyer.facades.brightness.Brightness object>
    Brightness proxy to plyer.facades.Brightness

plyer.call = <plyer.facades.call.Call object>
    Call proxy to :class plyer.facades.Call

plyer.camera = <plyer.facades.camera.Camera object>
    Camera proxy to plyer.facades.Camera

plyer.compass = <plyer.facades.compass.Compass object>
    Compass proxy to plyer.facades.Compass

plyer.cpu = <plyer.platforms.linux.cpu.LinuxCPU object>
    Processors proxy to plyer.facades.CPU

plyer.email = <plyer.platforms.linux.email.LinuxEmail object>
    Email proxy to plyer.facades.Email

plyer.filechooser = <plyer.platforms.linux.filechooser.LinuxFileChooser object>
    FileChooser proxy to plyer.facades.FileChooser

plyer.flash = <plyer.facades.flash.Flash object>
    Flash proxy to plyer.facades.Flash
```

```
plyer.gps = <plyer.facades.gps.GPS object>
    GPS proxy to plyer.facades.GPS

plyer.gravity = <plyer.facades.gravity.Gravity object>
    Gravity proxy to plyer.facades.Gravity

plyer.gyroscope = <plyer.facades.gyroscope.Gyroscope object>
    Gyroscope proxy to plyer.facades.Gyroscope

plyer.humidity = <plyer.facades.humidity.Humidity object>
    Humidity proxy to plyer.facades.Humidity

plyer.irblaster = <plyer.facades.irblaster.IrBlaster object>
    IrBlaster proxy to plyer.facades.IrBlaster

plyer.keystore = <plyer.facades.keystore.Keystore object>
    Keyring proxy to :class::plyer.facades.Keyring

plyer.light = <plyer.facades.light.Light object>
    Light proxy to plyer.facades.Light

plyer.notification = <plyer.facades.notification.Notification object>
    Notification proxy to plyer.facades.Notification

plyer.orientation = <plyer.platforms.linux.orientation.LinuxOrientation object>
    Orientation proxy to plyer.facades.Orientation

plyer.processors = <plyer.platforms.linux.processors.LinuxProcessors object>
    Processors proxy to plyer.facades.Processors

plyer.proximity = <plyer.facades.proximity.Proximity object>
    Proximity proxy to plyer.facades.Proximity

plyer.screenshot = <plyer.facades.screenshot.Screenshot object>
    Screenshot proxy to plyer.facades.Screenshot

plyer.sms = <plyer.facades.sms.Sms object>
    Sms proxy to plyer.facades.Sms

plyer.spatialorientation = <plyer.facades.spatialorientation.SpatialOrientation object>
    SpatialOrientation proxy to plyer.facades.SpatialOrientation

plyer.storagepath = <plyer.platforms.linux.storagepath.LinuxStoragePath object>
    StoragePath proxy to plyer.facades.StoragePath

plyer.stt = <plyer.facades.stt.STT object>
    Speech proxy to plyer.facades.STT

plyer.temperature = <plyer.facades.temperature.Temperature object>
    Temperature proxy to plyer.facades.Temperature

plyer.tts = <plyer.facades.tts.TTS object>
    TTS proxy to plyer.facades.TTS

plyer.uniqueid = <plyer.facades.uniqueid.UniqueID object>
    UniqueID proxy to plyer.facades.UniqueID

plyer.vibrator = <plyer.facades.vibrator.Vibrator object>
    Vibrator proxy to plyer.facades.Vibrator

plyer.wifi = <plyer.facades.wifi.Wifi object>
    Wifi proxy to plyer.facades.Wifi
```


CHAPTER 2

Facades

Interface of all the features available.

```
class plyer.facades.Accelerometer  
    Accelerometer facade.
```

```
    acceleration
```

```
        Property that returns values of the current acceleration sensors, as a (x, y, z) tuple. Returns (None, None, None) if no data is currently available.
```

```
    disable()
```

```
        Disable the accelerometer sensor.
```

```
    enable()
```

```
        Activate the accelerometer sensor. Throws an error if the hardware is not available or not implemented on.
```

```
class plyer.facades.Audio (file_path=None)  
    Audio facade.
```

```
    play()
```

```
        Play current recording.
```

```
    start()
```

```
        Start record.
```

```
    stop()
```

```
        Stop record.
```

```
class plyer.facades.Barometer  
    Barometer facade.
```

```
    Barometer sensor is used to measure the ambient air pressure in hPa.
```

```
    With method enable you can turn on pressure sensor and ‘disable’ method stops the sensor.
```

```
    Use property pressure to get current air pressure in hPa.
```

```
    New in version 1.2.5.
```

```
    Supported Platforms:: Android
```

disable()

Disable barometer sensor.

enable()

Enable barometer sensor.

pressure

Current air pressure in hPa.

class `plyer.facades.Battery`

Battery info facade.

get_state()

Public method for filling `battery.status` via platform-specific API in `plyer.platforms`.

status

Property that contains a dict with the following fields:

- **isCharging** (*bool*): Battery is charging
- **percentage** (*float*): Battery charge remaining

Warning: If any of the fields is not readable, it is set as `None`.

class `plyer.facades.Call`

Call facade.

dialcall()

Opens dialing interface.

makecall (*tel*)

Make calls using your device.

Parameters **tel** (*number*) – The reciever

class `plyer.facades.Camera`

Camera facade.

take_picture (*filename, on_complete*)

Ask the OS to capture a picture, and store it at filename.

When the capture is done, `on_complete` will be called with the filename as an argument. If the callback returns `True`, the filename will be unlinked.

Parameters

- **filename** (*str*) – Name of the image file
- **on_complete** (*callable*) – Callback that will be called when the operation is done

take_video (*filename, on_complete*)

Ask the OS to capture a video, and store it at filename.

When the capture is done, `on_complete` will be called with the filename as an argument. If the callback returns `True`, the filename will be unlinked.

Parameters

- **filename** (*str*) – Name of the video file
- **on_complete** (*callable*) – Callback that will be called when the operation is done

class `plyer.facades.Compass`

Compass facade.

New in version 1.2.0.

disable ()

Disable the compass sensor.

enable ()

Activate the compass sensor.

field

New in version 1.3.1.

Property that returns values of the current compass (magnetic field) sensors, as a (x, y, z) tuple. Returns (None, None, None) if no data is currently available.

field_uncalib

New in version 1.3.1.

Property that returns the current value of Uncalibrated Magnetic Field (without hard iron calibration) along with the iron bias estimation along the three axes.

get_field_uncalib ()

New in version 1.3.1.

orientation

WARNING:: This property is deprecated after API level 8. Use *compass.field* instead.

Property that returns values of the current compass (magnetic field) sensors, as a (x, y, z) tuple. Returns (None, None, None) if no data is currently available.

class `plyer.facades.Email`

Email facade.

send (*recipient=None, subject=None, text=None, create_chooser=None*)

Open an email client message send window, prepopulated with the given arguments.

Parameters

- **recipient** – Recipient of the message (str)
- **subject** – Subject of the message (str)
- **text** – Main body of the message (str)
- **create_chooser** – Whether to display a program chooser to handle the message (bool)

Note: `create_chooser` is only supported on Android

class `plyer.facades.FileChooser`

File Chooser facade.

choose_dir (**args, **kwargs*)

Open the directory chooser. Note that on Windows this is very limited. Consider writing your own chooser if you target that platform and are planning on using unsupported features.

open_file (**args, **kwargs*)

Open the file chooser in “open” mode.

save_file (**args, **kwargs*)

Open the file chooser in “save” mode. Confirmation will be asked when a file with the same name already exists.

class `plyer.facades.GPS`

GPS facade.

configure (*on_location*, *on_status=None*)

Configure the GPS object. This method should be called before `start()`.

Parameters

- **on_location** (*callable*, *multiples keys/value will be passed.*) – Function to call when receiving a new location
- **on_status** (*callable*, *args are "message-type", "status"*) – Function to call when a status message is received

Warning: The *on_location* and *on_status* callables might be called from another thread than the thread used for creating the GPS object.

start (*minTime=1000*, *minDistance=1*)

Start the GPS location updates. Expects 2 parameters:

minTime: milliseconds. (float) *minDistance*: meters. (float)

stop ()

Stop the GPS location updates.

class `plyer.facades.Gravity`

Gravity facade.

New in version 1.2.5.

Supported Platforms:: Android

disable ()

Disable the gravity sensor.

enable ()

Activate the gravity sensor. Throws an error if the hardware is not available or not implemented on.

gravity

Property that returns values of the current gravity force as a (x, y, z) tuple. Returns (None, None, None) if no data is currently available.

class `plyer.facades.Gyroscope`

Gyroscope facade.

New in version 1.3.1.

disable ()

Disable the Gyroscope sensor.

enable ()

Activate the Gyroscope sensor.

orientation

WARNING:: This property is deprecated after API Level 8. Use *gyroscope.rotation* instead.

Property that returns values of the current Gyroscope sensors, as a (x, y, z) tuple. Returns (None, None, None) if no data is currently available.

rotation

Property that returns the rate of rotation around the device's local X, Y and Z axis.

Along x-axis: angular speed around the X axis
 Along y-axis: angular speed around the Y axis
 Along z-axis: angular speed around the Z axis

Returns (None, None, None) if no data is currently available.

rotation_uncalib

Property that returns the current rate of rotation around the X, Y and Z axis. An estimation of the drift on each axis is reported as well.

Along x-axis: angular speed (w/o drift compensation) around the X axis
 Along y-axis: angular speed (w/o drift compensation) around the Y axis
 Along z-axis: angular speed (w/o drift compensation) around the Z axis

Along x-axis: estimated drift around X axis
 Along y-axis: estimated drift around Y axis
 Along z-axis: estimated drift around Z axis

Returns (None, None, None, None, None, None) if no data is currently available.

class `plyer.facades.IrBlaster`

Infrared blaster facade.

exists ()

Check if the device has an infrared emitter.

frequencies

Property which contains a list of frequency ranges supported by the device in the form:

`[(from1, to1), (from2, to2), ... (fromN, toN)]`

static `microseconds_to_periods` (*frequency, pattern*)

Convert a pattern from microseconds to period counts.

static `periods_to_microseconds` (*frequency, pattern*)

Convert a pattern from period counts to microseconds.

transmit (*frequency, pattern, mode='period'*)

Transmit an IR sequence.

Parameters

***frequency*: int** Carrier frequency for the IR transmission.

***pattern*: list[int]** Burst pair pattern to transmit.

***mode*: str, defaults to 'period'** Specifies the format of the pattern values. Can be 'period' or 'microseconds'.

class `plyer.facades.Light`

Light facade.

Light sensor measures the ambient light level(illumination) in lx. Common uses include controlling screen brightness.

With method *enable* you can turn on the sensor and *disable* method stops the sensor.

Use property *illumination* to get current illumination in lx.

New in version 1.2.5.

Supported Platforms:: Android

disable ()

Disable light sensor.

enable()

Enable light sensor.

illumination

Current illumination in lx.

class `plyer.facades.Orientation`

Orientation facade.

set_landscape (*reverse=False*)

Rotate the app to a landscape orientation.

Parameters **reverse** – If True, uses the opposite of the natural orientation.

set_portrait (*reverse=False*)

Rotate the app to a portrait orientation.

Parameters **reverse** – If True, uses the opposite of the natural orientation.

set_sensor (*mode='any'*)

Rotate freely following sensor information from the device.

Parameters **mode** – The rotation mode, should be one of ‘any’ (rotate to any orientation), ‘landscape’ (choose nearest landscape mode) or ‘portrait’ (choose nearest portrait mode). Defaults to ‘any’.

class `plyer.facades.Notification`

Notification facade.

notify (*title="", message="", app_name="", app_icon="", timeout=10, ticker="", toast=False*)

Send a notification.

Parameters

- **title** (*str*) – Title of the notification
- **message** (*str*) – Message of the notification
- **app_name** (*str*) – Name of the app launching this notification
- **app_icon** (*str*) – Icon to be displayed along with the message
- **timeout** (*int*) – time to display the message for, defaults to 10
- **ticker** (*str*) – text to display on status bar as the notification arrives
- **toast** (*bool*) – simple Android message instead of full notification

Note: When called on Windows, `app_icon` has to be a path to a file in .ICO format.

New in version 1.0.0.

Changed in version 1.4.0: Add ‘toast’ keyword argument

class `plyer.facades.Proximity`

Proximity facade.

The proximity sensor is commonly used to determine distance whether phone is close to your head. Commonly is used when you have a call and you stick your phone with your head. Then screen of phone turns off.

Use method *enable* to turn on proximity sensor and method *disable* for turn off.

To check if some object (or your head) is near sensor check values from property *proximity*. It returns *True* when object is close.

New in version 1.2.5.

Supported Platforms::Android

disable()

Disable the proximity sensor.

enable()

Enable the proximity sensor.

proximity

Return True or False depending if there is an object or not.

Returns True if there is an object. Otherwise False.

class `plyer.facades.Sms`

Sms facade.

send(*recipient*, *message*)

Send SMS or open SMS interface.

Parameters

- **recipient** (*number*) – The reveiver
- **message** (*str*) – the message

class `plyer.facades.TTS`

TextToSpeech facade.

speak(*message*=")

Use text to speech capabilities to speak the message.

Parameters **message** (*str*) – What to speak

class `plyer.facades.UniqueID`

UniqueID facade.

get_uid()

Public method for receiving unique ID via platform-specific API in `plyer.platforms`.

id

Property that returns the unique id of the platform.

class `plyer.facades.Vibrator`

Vibration facade.

cancel()

Cancels any current vibration, and stops the vibrator.

exists()

Check if the device has a vibrator. Returns True or False.

pattern(*pattern*=(0, 1), *repeat*=-1)

Ask the vibrator to vibrate with the given pattern, with an optional repeat.

Parameters

- **pattern** – Pattern to vibrate with. Should be a list of times in seconds. The first number is how long to wait before vibrating, and subsequent numbers are times to vibrate and not vibrate alternately. Defaults to [0, 1].
- **repeat** – Index at which to repeat the pattern. When the vibration pattern reaches this index, it will start again from the beginning. Defaults to -1, which means no repeat.

vibrate (*time=1*)

Ask the vibrator to vibrate for the given period.

Parameters **time** – Time to vibrate for, in seconds. Default is 1.

class `plyer.facades.Wifi`

Wifi Facade.

connect (*network, parameters, interface=None*)

Method to connect to some network.

disable ()

Wifi interface power state is set to “OFF”.

disconnect (*interface=None*)

To disconnect from some network.

enable ()

Wifi interface power state is set to “ON”.

get_available_wifi ()

Returns a list of all the available wifi.

get_network_info (*name*)

Return a dictionary of secified network.

interfaces

List all available WiFi interfaces.

New in version 1.4.0.

is_connected (*interface=None*)

Return connection state of WiFi interface.

New in version 1.4.0.

is_enabled ()

Return enabled status of WiFi hardware.

start_scanning (*interface=None*)

Turn on scanning.

class `plyer.facades.Flash`

Flash facade.

off ()

Deactiavte the flash

on ()

Activate the flash

release ()

Release any access to the Flash / Camera. Call this when you’re done using the Flash. This will release the Camera, and stop any process.

Next call to `_on` will reactivate it.

class `plyer.facades.CPU`

Facade providing info about sockets, physical and logical number of processors.

cache

Property that contains the count of L1, L2, L3 caches in the system as a dictionary `{‘L1’: int, ‘L2’: int, ‘L3’: int}`.

logical

Property that contains the total number of logical cores (max thread count) in the system.

Note: *sockets * cores per socket * threads per core*

numa

Property that contains the count of NUMA nodes in the system.

Note: https://en.wikipedia.org/wiki/Non-uniform_memory_access

physical

Property that contains the total number of physical cores (max core count) in the system.

Note: *sockets * cores per socket*

sockets

Property that contains the count of CPU sockets.

class plyer.facades.Temperature

Temperature facade.

Temperature sensor is used to measure the ambient room temperature in degrees Celsius (°C) With method *enable* you can turn on temperature sensor and 'disable' method stops the sensor. Use property *temperature* to get ambient air temperature in degree C.

New in version 1.2.5.

Supported Platforms:: Android

disable()

Disable temperature sensor.

enable()

Enable temperature sensor.

temperature

Current air temperature in degree C.

class plyer.facades.Humidity

Humidity facade. Humidity sensor returns value of humidity. With method *enable* you can turn on Humidity sensor and 'disable' method stops the sensor. Use property *tell* to get humidity value.

disable()

Disable Humidity sensor.

enable()

Enable Humidity sensor.

tell

Current humidity

class plyer.facades.SpatialOrientation

Spatial Orientation facade.

Computes the device's orientation based on the rotation matrix.

New in version 1.3.1.

disable_listener()

Disable the orientation sensor.

enable_listener()

Enable the orientation sensor.

orientation

Property that returns values of the current device orientation as a (azimuth, pitch, roll) tuple.

Azimuth, angle of rotation about the -z axis. This value represents the angle between the device's y axis and the magnetic north pole. The range of values is $-\pi$ to π .

Pitch, angle of rotation about the x axis. This value represents the angle between a plane parallel to the device's screen and a plane parallel to the ground. The range of values is $-\pi$ to π .

Roll, angle of rotation about the y axis. This value represents the angle between a plane perpendicular to the device's screen and a plane perpendicular to the ground. The range of values is $-\pi/2$ to $\pi/2$.

Returns (None, None, None) if no data is currently available.

Supported Platforms:: Android

class plyer.facades.**Brightness**

Brightness facade.

current_level()

Know the current level of device's brightness.

set_level(level)

Adjust the brightness of the screen. Minimum brightness level:: 1 Maximum brightness level:: 100

Parameters level (int) – New level of brightness between 1 and 100

class plyer.facades.**Processors**

Number of Processors info facade.

status

Property that contains a dict with the following fields:

- **Number_of_Processors (int)**: Number of Processors in the system

<p>Warning: If any of the fields is not readable, it is set as None.</p>

class plyer.facades.**StoragePath**

StoragePath facade.

get_application_dir()

Get the path of the directory holding application files.

get_documents_dir()

Get the path of standard directory in which to place documents that have been created by the user.

get_downloads_dir()

Get the path of standard directory in which to place files that have been downloaded by the user.

get_external_storage_dir()

Get the path of primary shared or external storage directory.

get_home_dir()

Get the path of home directory of current user.

```

get_music_dir()
    Get the path of standard directory in which to place any audio files that should be in the regular list of
    music for the user.

get_pictures_dir()
    Standard directory in which to place pictures that are available to the user.

get_root_dir()
    Get the path of root of the “system” partition holding the core OS.

get_sdcard_dir()
    Get the path of external SD card.

    New in version 1.4.0.

get_videos_dir()
    Get the path of standard directory in which to place videos that are available to the user.

class plyer.facades.Bluetooth
    Bluetooth facade.

    info
        Property that returns the info (currently status) of the bluetooth.

class plyer.facades.Screenshot (file_path=None)
    Screenshot facade.

class plyer.facades.STT
    Speech to text facade.

    errors = []
        List of errors found while listening.

    exist()
        Returns a boolean for speech recognition availability.

    language
        Return current language.

    listening = False
        Current state of listening.

    partial_results = []
        List of results found while the listener is still being active.

    prefer_offline = True
        Preference whether to use offline language package necessary for each platform dependant implementation
        or online API.

    results = []
        List of sentences found while listening. It may consist of many similar and possible sentences that was
        recognition program.

    start()
        Start listening.

    stop()
        Stop listening.

    supported_languages
        Return list of supported languages used in recognition.

```


CHAPTER 3

Indices and tables

- `genindex`
- `modindex`
- `search`

p

`plyer`, [1](#)
`plyer.facades`, [4](#)

A

acceleration (*plyer.facades.Accelerometer attribute*), 5
 Accelerometer (*class in plyer.facades*), 5
 accelerometer (*in module plyer*), 3
 Audio (*class in plyer.facades*), 5
 audio (*in module plyer*), 3

B

Barometer (*class in plyer.facades*), 5
 barometer (*in module plyer*), 3
 Battery (*class in plyer.facades*), 6
 battery (*in module plyer*), 3
 Bluetooth (*class in plyer.facades*), 15
 bluetooth (*in module plyer*), 3
 Brightness (*class in plyer.facades*), 14
 brightness (*in module plyer*), 3

C

cache (*plyer.facades.CPU attribute*), 12
 Call (*class in plyer.facades*), 6
 call (*in module plyer*), 3
 Camera (*class in plyer.facades*), 6
 camera (*in module plyer*), 3
 cancel () (*plyer.facades.Vibrator method*), 11
 choose_dir () (*plyer.facades.FileChooser method*), 7
 Compass (*class in plyer.facades*), 6
 compass (*in module plyer*), 3
 configure () (*plyer.facades.GPS method*), 8
 connect () (*plyer.facades.Wifi method*), 12
 CPU (*class in plyer.facades*), 12
 cpu (*in module plyer*), 3
 current_level () (*plyer.facades.Brightness method*), 14

D

dialcall () (*plyer.facades.Call method*), 6
 disable () (*plyer.facades.Accelerometer method*), 5
 disable () (*plyer.facades.Barometer method*), 5

disable () (*plyer.facades.Compass method*), 7
 disable () (*plyer.facades.Gravity method*), 8
 disable () (*plyer.facades.Gyroscope method*), 8
 disable () (*plyer.facades.Humidity method*), 13
 disable () (*plyer.facades.Light method*), 9
 disable () (*plyer.facades.Proximity method*), 11
 disable () (*plyer.facades.Temperature method*), 13
 disable () (*plyer.facades.Wifi method*), 12
 disable_listener ()
 (*plyer.facades.SpatialOrientation method*), 13
 disconnect () (*plyer.facades.Wifi method*), 12

E

Email (*class in plyer.facades*), 7
 email (*in module plyer*), 3
 enable () (*plyer.facades.Accelerometer method*), 5
 enable () (*plyer.facades.Barometer method*), 6
 enable () (*plyer.facades.Compass method*), 7
 enable () (*plyer.facades.Gravity method*), 8
 enable () (*plyer.facades.Gyroscope method*), 8
 enable () (*plyer.facades.Humidity method*), 13
 enable () (*plyer.facades.Light method*), 9
 enable () (*plyer.facades.Proximity method*), 11
 enable () (*plyer.facades.Temperature method*), 13
 enable () (*plyer.facades.Wifi method*), 12
 enable_listener ()
 (*plyer.facades.SpatialOrientation method*), 14
 errors (*plyer.facades.STT attribute*), 15
 exist () (*plyer.facades.STT method*), 15
 exists () (*plyer.facades.IrBlaster method*), 9
 exists () (*plyer.facades.Vibrator method*), 11

F

field (*plyer.facades.Compass attribute*), 7
 field_uncalib (*plyer.facades.Compass attribute*), 7
 FileChooser (*class in plyer.facades*), 7
 filechooser (*in module plyer*), 3

Flash (*class in plyer.facades*), 12
flash (*in module plyer*), 3
frequencies (*plyer.facades.IrBlaster attribute*), 9

G

get_application_dir() (*plyer.facades.StoragePath method*), 14
get_available_wifi() (*plyer.facades.Wifi method*), 12
get_documents_dir() (*plyer.facades.StoragePath method*), 14
get_downloads_dir() (*plyer.facades.StoragePath method*), 14
get_external_storage_dir() (*plyer.facades.StoragePath method*), 14
get_field_uncalib() (*plyer.facades.Compass method*), 7
get_home_dir() (*plyer.facades.StoragePath method*), 14
get_music_dir() (*plyer.facades.StoragePath method*), 14
get_network_info() (*plyer.facades.Wifi method*), 12
get_pictures_dir() (*plyer.facades.StoragePath method*), 15
get_root_dir() (*plyer.facades.StoragePath method*), 15
get_sdcard_dir() (*plyer.facades.StoragePath method*), 15
get_state() (*plyer.facades.Battery method*), 6
get_uid() (*plyer.facades.UniqueID method*), 11
get_videos_dir() (*plyer.facades.StoragePath method*), 15
GPS (*class in plyer.facades*), 7
gps (*in module plyer*), 3
Gravity (*class in plyer.facades*), 8
gravity (*in module plyer*), 4
gravity (*plyer.facades.Gravity attribute*), 8
Gyroscope (*class in plyer.facades*), 8
gyroscope (*in module plyer*), 4

H

Humidity (*class in plyer.facades*), 13
humidity (*in module plyer*), 4

I

id (*plyer.facades.UniqueID attribute*), 11
illumination (*plyer.facades.Light attribute*), 10
info (*plyer.facades.Bluetooth attribute*), 15
interfaces (*plyer.facades.Wifi attribute*), 12
IrBlaster (*class in plyer.facades*), 9
irblaster (*in module plyer*), 4
is_connected() (*plyer.facades.Wifi method*), 12
is_enabled() (*plyer.facades.Wifi method*), 12

K

keystore (*in module plyer*), 4

L

language (*plyer.facades.STT attribute*), 15
Light (*class in plyer.facades*), 9
light (*in module plyer*), 4
listening (*plyer.facades.STT attribute*), 15
logical (*plyer.facades.CPU attribute*), 12

M

makecall() (*plyer.facades.Call method*), 6
microseconds_to_periods() (*plyer.facades.IrBlaster static method*), 9

N

Notification (*class in plyer.facades*), 10
notification (*in module plyer*), 4
notify() (*plyer.facades.Notification method*), 10
numa (*plyer.facades.CPU attribute*), 13

O

off() (*plyer.facades.Flash method*), 12
on() (*plyer.facades.Flash method*), 12
open_file() (*plyer.facades.FileChooser method*), 7
Orientation (*class in plyer.facades*), 10
orientation (*in module plyer*), 4
orientation (*plyer.facades.Compass attribute*), 7
orientation (*plyer.facades.Gyroscope attribute*), 8
orientation (*plyer.facades.SpatialOrientation attribute*), 14

P

partial_results (*plyer.facades.STT attribute*), 15
pattern() (*plyer.facades.Vibrator method*), 11
periods_to_microseconds() (*plyer.facades.IrBlaster static method*), 9
physical (*plyer.facades.CPU attribute*), 13
play() (*plyer.facades.Audio method*), 5
plyer (*module*), 1
plyer.facades (*module*), 4
prefer_offline (*plyer.facades.STT attribute*), 15
pressure (*plyer.facades.Barometer attribute*), 6
Processors (*class in plyer.facades*), 14
processors (*in module plyer*), 4
Proximity (*class in plyer.facades*), 10
proximity (*in module plyer*), 4
proximity (*plyer.facades.Proximity attribute*), 11

R

release() (*plyer.facades.Flash method*), 12
results (*plyer.facades.STT attribute*), 15
rotation (*plyer.facades.Gyroscope attribute*), 8

rotation_uncalib (*plyer.facades.Gyroscope attribute*), 9

S

save_file() (*plyer.facades.FileChooser method*), 7
Screenshot (*class in plyer.facades*), 15
screenshot (*in module plyer*), 4
send() (*plyer.facades.Email method*), 7
send() (*plyer.facades.Sms method*), 11
set_landscape() (*plyer.facades.Orientation method*), 10
set_level() (*plyer.facades.Brightness method*), 14
set_portrait() (*plyer.facades.Orientation method*), 10
set_sensor() (*plyer.facades.Orientation method*), 10
Sms (*class in plyer.facades*), 11
sms (*in module plyer*), 4
sockets (*plyer.facades.CPU attribute*), 13
SpatialOrientation (*class in plyer.facades*), 13
spatialorientation (*in module plyer*), 4
speak() (*plyer.facades.TTS method*), 11
start() (*plyer.facades.Audio method*), 5
start() (*plyer.facades.GPS method*), 8
start() (*plyer.facades.STT method*), 15
start_scanning() (*plyer.facades.Wifi method*), 12
status (*plyer.facades.Battery attribute*), 6
status (*plyer.facades.Processors attribute*), 14
stop() (*plyer.facades.Audio method*), 5
stop() (*plyer.facades.GPS method*), 8
stop() (*plyer.facades.STT method*), 15
StoragePath (*class in plyer.facades*), 14
storagepath (*in module plyer*), 4
STT (*class in plyer.facades*), 15
stt (*in module plyer*), 4
supported_languages (*plyer.facades.STT attribute*), 15

T

take_picture() (*plyer.facades.Camera method*), 6
take_video() (*plyer.facades.Camera method*), 6
tell (*plyer.facades.Humidity attribute*), 13
Temperature (*class in plyer.facades*), 13
temperature (*in module plyer*), 4
temperature (*plyer.facades.Temperature attribute*), 13
transmit() (*plyer.facades.IrBlaster method*), 9
TTS (*class in plyer.facades*), 11
tts (*in module plyer*), 4

U

UniqueID (*class in plyer.facades*), 11
uniqueid (*in module plyer*), 4

V

vibrate() (*plyer.facades.Vibrator method*), 11
Vibrator (*class in plyer.facades*), 11
vibrator (*in module plyer*), 4

W

Wifi (*class in plyer.facades*), 12
wifi (*in module plyer*), 4